

# CBCS SCHEME

17EE82

## Eighth Semester B.E. Degree Examination, July/August 2021 Industrial Drives and Applications

Time: 3 hrs.

Max. Marks: 100

**Note: Answer any FIVE full questions.**

1. a. Explain the speed control conventions and four quadrant operation of motor driving a hoist load. (08 Marks)  
b. Explain different power modulators that are used in drive system. (04 Marks)  
c. A drive has the following parameters  $J = 10 \text{ kg-m}^2$ ,  $T = 15 + 0.05N$ ,  $T_l = 5 + 0.06N \text{ N-m}$ . Initially drive is working in steady state. Now the drive is braked by electrical braking. Torque of the motor during braking is given by  $T = -10 - 0.04N \text{ N-m}$ . Calculate the time taken to stop. (08 Marks)
2. a. Obtain the fundamental torque equation of a motor load system. (06 Marks)  
b. Explain closed loop speed control of drives. (06 Marks)  
c. A weight of 500kg is being lifted up at a uniform speed of 1.5 m/sec by a winch driven by a motor running at a speed of 1000rpm. Moment of inertia of the motor and winch are 0.5 and 0.3  $\text{kg-m}^2$  respectively. Calculate the motor torque and equivalent moment of inertia referred to motor shaft. In the absence of weight motor develops a torque of 100Nm when running at 1000rpm. Assume efficiency of winch = 100%. (08 Marks)
3. a. Develop an expression of overloading factor  $K$  while selecting the motor rating for short time duty. (10 Marks)  
b. A 220V, 960rpm, 12.8A separately excited dc motor has  $R_a = 2\Omega$ ,  $L_a = 150\text{mH}$ . It is fed from a 1  $\phi$  half controlled rectifier with an AC source voltage of 230V, 50Hz. Calculate:  
i) Motor torque for firing angle =  $60^\circ$  and speed = 600rpm  
ii) Motor speed for firing angle =  $60^\circ$  and torque = 20Nm. (10 Marks)
4. a. Explain chopper control of DC series motor for motoring and regenerative operation. (10 Marks)  
b. Select the motor for driving the equipment which has the load curve shown in Fig.Q.4(b). Last 46 sec torque is constant at 8N-m. (10 Marks)




Fig.Q.4(b)

- 5 a. Describe the operation of induction motor operating with unbalanced voltages. (10 Marks)  
 b. A 400V, Y connected, 3 phase, 6 pole, 50Hz induction motor has following parameters referred to stator:  $R_s = R'_r = 1\Omega$ ,  $X_s = X'_r = 2\Omega$ . For regenerative braking operation of this motor determine:  
 i) Maximum overhauling torque it can hold and range of speed for safe operation.  
 ii) Speed at which it will hold an overhauling load with a torque of 100N-m. (10 Marks)
- 6 a. Explain variable frequency control of induction motor with relevant diagram. (08 Marks)  
 b. A 2200V, 2600kW, 735rpm, 50Hz, 8pole, 3phase squirrel cage induction motor has following parameters referred to the stator  $R_s = 0.075\Omega$ ,  $R'_r = 0.1\Omega$ ,  $X_s = 0.45\Omega$ ,  $X'_r = 0.55\Omega$  stator winding is delta connected.  
 i) Calculate starting torque and maximum torque as a ratio of rated torque, if the motor is started by star delta starting what is the maximum value of line current during starting?  
 ii) Calculate transformation ratio of an auto transformer so as to limit the maximum starting current to twice the rated value. (12 Marks)
- 7 a. Explain the braking and multiquadrant operation of voltage source inverter fed induction motor. (10 Marks)  
 b. Explain pull in process in synchronous motor operation from fixed frequency supply. (10 Marks)
- 8 a. Describe the current source inverter control of induction motor. (10 Marks)  
 b. For inverter fed induction motor drive calculate approximate values of  
 i) Speed for a frequency of 30Hz and 80% of full load torque  
 ii) Frequency for a speed of 40Hz and speed of 1100rpm.  
 Given data for induction motor:  
 Y connected, 400V, 50Hz, 4 pole, 1370rpm. (10 Marks)
- 9 a. Explain the self controlled synchronous motor drive, employing load commutated thyristor inverter. (10 Marks)  
 b. Explain brushless DC motor drive for servo applications. (10 Marks)
- 10 a. With a neat block diagram, explain the true synchronous mode variable frequency control of multiple synchronous motor drive. (10 Marks)  
 b. Explain the drive requirements of cranes and hoist drive. (10 Marks)

\*\*\*\*\*